



Tornado T2

Tornado T2 23W WW E27 220-240V 1PF/6

Tornado has outstanding brightness which makes your colors appear more Vivid. It fits everywhere due to its compact design With comprehensive product range, it allows easy replacement of incandescent lamps all the way

Product data

General Information	
Cap-Base	E27 [E27]
Nominal Lifetime (Nom)	10000 h
Switching Cycle	10000X
Light Technical	
Color Code	827 [CCT of 2700K]
Luminous Flux (Nom)	1570 lm
Luminous Flux (Rated) (Nom)	1570 lm
Color Designation	Warm White (WW)
Lumen Maintenance 2000 h (Nom)	88 %
Chromaticity Coordinate X (Nom)	463
Chromaticity Coordinate Y (Nom)	420
Correlated Color Temperature (Nom)	2700 K
Luminous Efficacy (Rated) (Nom)	67 lm/W
Color Rendering Index (Nom)	82
LLMF At End Of Nominal Lifetime (Nom)	65 %
Operating and Electrical	
Input Frequency	50 or 60 Hz
Power (Rated) (Nom)	23.0 W
Lamp Current (Nom)	170 mA
Wattage Equivalent	110 W
Starting Time (Nom)	0.3 s


Warm Up Time to 60% Light (Min)	5 s			
Warm Up Time to 60% Light (Max)	40 s			
Power Factor (Nom)	0.6			
Voltage (Nom)	220-240 V			
Controls and Dimming				
Dimmable	No			
Annual and Analization				
Approval and Application				
Energy Efficiency Label (EEL)	A			
Mercury (Hg) Content (Max)	2.5 mg			
Mercury (Hg) Content (Nom)	2 mg			
Energy Consumption kWh/1000 h	23 kWh			
Product Data				
Full product code	872790092594400			
Order product name	Tornado T2 23W WW E27 220-240V 1PF/6			
EAN/UPC - Product	8727900925944			
Order code	929689154101			
Numerator - Quantity Per Pack	1			
Numerator - Packs per outer box	6			
Material Nr. (12NC)	929689154101			
Net Weight (Piece)	0.077 kg			

Datasheet, 2017, November 20 data subject to change

Warnings and Safety

- Breaking a lamp is extremely unlikely to have any impact on your health. If a lamp breaks, ventilate the room for 30 minutes and remove the parts, preferably with gloves. Put them in a closed plastic bag and take it to your local waste facilities for recycling. Do not use a vacuum cleaner.
- Compact fluorescent lamps have to be treated as special waste, they must be taken to your local waste facilities for recycling. The European Lighting Industry has set up an infrastructure, capable of recycling mercury, other metals, glass etc.

Dimensional drawing



QSPIR-F Erp 23W/827 E27 220-240V 50/60Hz

Product	D (max)	C (max)	F (max)
Tornado T2 23W WW E27 220-240V 1PF/6	61.5 mm	118.5 mm	50.5 mm

